Booting linux on ESP32s3

Sources:

- https://github.com/jcmvbkbc/xtensa-dynconfig/tree/original
- https://github.com/jcmvbkbc/config-esp32s3
- https://github.com/jcmvbkbc/esp-idf/tree/linux-5.0.1
- https://github.com/jcmvbkbc/linux-xtensa/tree/xtensa-6.4-esp32
- https://github.com/jcmvbkbc/binutils-gdb-xtensa/tree/xtensa-2.40-fdpic
- https://github.com/jcmvbkbc/gcc-xtensa/tree/xtensa-14-fdpic
- https://github.com/jcmvbkbc/uclibc-ng-xtensa/tree/xtensa-fdpic
- https://github.com/jcmvbkbc/buildroot/tree/xtensa-2023.08-fdpic
- https://github.com/jcmvbkbc/crosstool-NG/tree/xtensa-fdpic

Scripts with all steps below: https://github.com/jcmvbkbc/esp32-linux-build

Example kernel and rootfs images built from the above sources as well as a toolchain archive: http://jcmvbkbc.spb.ru/~dumb/tmp/202305161729/

Build toolchain dynconfig library and export XTENSA_GNU_CONFIG for use by the toolchain

```
$ git clone https://github.com/jcmvbkbc/xtensa-dynconfig -b original
$ git clone https://github.com/jcmvbkbc/config-esp32s3 esp32s3
$ make -C xtensa-dynconfig ORIG=1 CONF_DIR=`pwd` esp32s3.so
$ export XTENSA_GNU_CONFIG=`pwd`/xtensa-dynconfig/esp32s3.so # make sure
this environment variable is set for all commands involving building or
using the toolchain
```

Build the toolchain

```
$ git clone https://github.com/jcmvbkbc/crosstool-NG.git -b xtensa-fdpic
$ pushd crosstool-NG
$ ./bootstrap && ./configure --enable-local && make
$ ./ct-ng xtensa-esp32s3-linux-uclibcfdpic
$ CT_PREFIX=`pwd`/builds nice ./ct-ng build
$ popd
```

It doesn't complete successfully ATM, failing with the following message, but it builds and installs everything that's important.

```
...
[INFO ]  Installing final gcc compiler: done in 572.47s (at 29:47)
[INFO ]  ==================================================================
[INFO ]  Checking dynamic linker symlinks
[EXTRA]    Checking dynamic linker for multilib ''
[ERROR]    collect2: error: ld returned 1 exit status
```

```
[ERROR]
[ERROR]  >>
[ERROR]  >>  Build failed in step 'Checking dynamic linker symlinks'
[ERROR]  >>        called in step '(top-level)'
[ERROR]  >>
[ERROR]  >>  Error happened in: CT_DoExecLog[scripts/functions@377]
[ERROR]  >>        called from: CT__FixupLDSO[scripts/functions@1695]
[ERROR]  >>        called from: CT_IterateMultilibs[scripts/functions@1608]
[ERROR]  >>        called from: CT_MultilibFixupLDSO[scripts/functions@1761]
[ERROR]  >>        called from: uClibc_ng_post_cc[scripts/build/libc/uClibc-
ng.sh@335]
[ERROR]  >>        called from: do_libc_post_cc[scripts/build/libc.sh@38]
[ERROR]  >>        called from: main[scripts/crosstool-NG.sh@697]
[ERROR]  >>
...
```

Build the rootfs and kernel image

```
$ git clone https://github.com/jcmvbkbc/buildroot -b xtensa-2023.08-fdpic
$ nice make -C buildroot O=`pwd`/build-buildroot-esp32s3 esp32s3_defconfig
$ buildroot/utils/config --file build-buildroot-esp32s3/.config --set-str
TOOLCHAIN_EXTERNAL_PATH `pwd`/crosstool-NG/builds/xtensa-esp32s3-linux-
uclibcfdpic
$ buildroot/utils/config --file build-buildroot-esp32s3/.config --set-str
TOOLCHAIN_EXTERNAL_PREFIX '$(ARCH)-esp32s3-linux-uclibcfdpic'
$ buildroot/utils/config --file build-buildroot-esp32s3/.config --set-str
TOOLCHAIN_EXTERNAL_CUSTOM_PREFIX '$(ARCH)-esp32s3-linux-uclibcfdpic'
$ nice make -C buildroot O=`pwd`/build-buildroot-esp32s3
```

Build and flash the bootloader, flash kernel and rootfs images

```
$ git clone https://github.com/jcmvbkbc/esp-idf -b linux-5.0.1
$ pushd esp-idf
$ . export.sh
$ cd examples/get-started/linux_boot
$ idf.py set-target esp32s3
$ cp sdkconfig.defaults.esp32s3 sdkconfig
$ idf.py build
$ idf.py flash
$ popd
$ parttool.py write_partition --partition-name linux  --input build-
buildroot-esp32s3/images/xipImage
$ parttool.py write_partition --partition-name rootfs --input build-
buildroot-esp32s3/images/rootfs.cramfs
$ parttool.py write_partition --partition-name etc    --input build-
buildroot-esp32s3/images/etc.jffs2
```

The result

```
ESP-ROM:esp32s3-20210327
Build:Mar 27 2021
rst:0x1 (POWERON),boot:0x8 (SPI_FAST_FLASH_BOOT)
SPIWP:0xee
mode:DIO, clock div:1
load:0x3fce3810,len:0x10a0
load:0x403c9700,len:0xa24
load:0x403cc700,len:0x2d04
entry 0x403c988c
I (73) octal_psram: vendor id    : 0x0d (AP)
I (73) octal_psram: dev id       : 0x02 (generation 3)
I (74) octal_psram: density      : 0x03 (64 Mbit)
I (78) octal_psram: good-die     : 0x01 (Pass)
I (83) octal_psram: Latency      : 0x01 (Fixed)
I (89) octal_psram: VCC          : 0x01 (3V)
I (93) octal_psram: SRF          : 0x01 (Fast Refresh)
I (99) octal_psram: BurstType    : 0x01 (Hybrid Wrap)
I (105) octal_psram: BurstLen     : 0x01 (32 Byte)
I (110) octal_psram: Readlatency  : 0x02 (10 cycles@Fixed)
I (117) octal_psram: DriveStrength: 0x00 (1/1)
I (122) esp_psram: Found 8MB PSRAM device
I (126) esp_psram: Speed: 80MHz
I (130) cpu_start: Pro cpu up.
I (134) cpu_start: Starting app cpu, entry point is 0x40375344
I (0) cpu_start: App cpu up.
I (593) esp_psram: SPI SRAM memory test OK
I (602) cpu_start: Pro cpu start user code
I (602) cpu_start: cpu freq: 160000000 Hz
I (602) cpu_start: Application information:
I (605) cpu_start: Project name:     linux_boot
I (610) cpu_start: App version:      v5.0.1-4-g680509ab40d1
I (617) cpu_start: Compile time:     May  7 2023 16:29:12
I (623) cpu_start: ELF file SHA256:  a110e4309915b853...
I (629) cpu_start: ESP-IDF:          v5.0.1-4-g680509ab40d1
I (635) cpu_start: Min chip rev:     v0.0
I (640) cpu_start: Max chip rev:     v0.99
I (644) cpu_start: Chip rev:         v0.1
I (649) heap_init: Initializing. RAM available for dynamic allocation:
I (656) heap_init: At 3FC958C0 len 00053E50 (335 KiB): D/IRAM
I (663) heap_init: At 3FCE9710 len 00005724 (21 KiB): STACK/DRAM
I (669) heap_init: At 3FCF0000 len 00008000 (32 KiB): DRAM
I (676) heap_init: At 600FE010 len 00001FF0 (7 KiB): RTCRAM
I (682) esp_psram: Adding pool of 8192K of PSRAM memory to heap allocator
I (690) spi_flash: detected chip: generic
I (694) spi_flash: flash io: dio
I (699) cpu_start: Starting scheduler on PRO CPU.
I (0) cpu_start: Starting scheduler on APP CPU.
I (719) esp_psram: Reserving pool of 32K of internal memory for DMA/internal
```

```
allocations
ptr = 0x42830000
ptr = 0x42b30000
[    0.000000] Ignoring boot parameters at (ptrval)
[    0.000000] Linux version 6.3.0-00022-g5d8354462a70 (jcmvbkbc@octofox)
(xtensa-dc233c-elf-gcc (GCC) 13.1.0, GNU ld (GNU Binutils) 2.40) #39 PREEMPT
Sun May  7 16:35:44 PDT 2023
[    0.000000] config ID: c2f0fffe:23090f1f
[    0.000000] earlycon: esp32uart0 at MMIO32 0x60000000 (options
'115200n8')
[    0.000000] printk: bootconsole [esp32uart0] enabled
[    0.000000] **********************************************************
[    0.000000] **   NOTICE NOTICE NOTICE NOTICE NOTICE NOTICE NOTICE   **
[    0.000000] **                                                      **
[    0.000000] ** This system shows unhashed kernel memory addresses   **
[    0.000000] ** via the console, logs, and other interfaces. This    **
[    0.000000] ** might reduce the security of your system.            **
[    0.000000] **                                                      **
[    0.000000] ** If you see this message and you are not debugging    **
[    0.000000] ** the kernel, report this immediately to your system   **
[    0.000000] ** administrator!                                       **
[    0.000000] **                                                      **
[    0.000000] **   NOTICE NOTICE NOTICE NOTICE NOTICE NOTICE NOTICE   **
[    0.000000] **********************************************************
[    0.000000] Zone ranges:
[    0.000000]   Normal   [mem 0x000000003c030000-0x000000003c82ffff]
[    0.000000] Movable zone start for each node
[    0.000000] Early memory node ranges
[    0.000000]   node   0: [mem 0x000000003c030000-0x000000003c82ffff]
[    0.000000] Initmem setup node 0 [mem
0x000000003c030000-0x000000003c82ffff]
[    0.000000] pcpu-alloc: s0 r0 d32768 u32768 alloc=1*32768
[    0.000000] pcpu-alloc: [0] 0
[    0.000000] Built 1 zonelists, mobility grouping off.  Total pages: 2032
[    0.000000] Kernel command line:
earlycon=esp32uart,mmio32,0x60000000,115200n8 console=ttyS0,115200n8 debug
rw root=mtd:data no_hash_pointers
[    0.000000] Dentry cache hash table entries: 1024 (order: 0, 4096 bytes,
linear)
[    0.000000] Inode-cache hash table entries: 1024 (order: 0, 4096 bytes,
linear)
[    0.000000] mem auto-init: stack:off, heap alloc:off, heap free:off
[    0.000000] virtual kernel memory layout:
[    0.000000]     lowmem  : 0x3c030000 - 0x3c830000  (    8 MB)
[    0.000000]     .text   : 0x42830000 - 0x429e0d28  ( 1731 kB)
[    0.000000]     .rodata : 0x429e1000 - 0x42a1f000  (  248 kB)
[    0.000000]     .data   : 0x3c030000 - 0x3c0a9420  (  485 kB)
[    0.000000]     .init   : 0x3c0a9420 - 0x3c0adf00  (   18 kB)
[    0.000000]     .bss    : 0x3c0adf00 - 0x3c0e1988  (  206 kB)
```

```
[    0.000000] Memory: 7332K/8192K available (1731K kernel code, 485K
rwdata, 248K rodata, 88K init, 206K bss, 860K reserved, 0K cma-reserved)
[    0.000000] SLUB: HWalign=16, Order=0-3, MinObjects=0, CPUs=1, Nodes=1
[    0.000000] rcu: Preemptible hierarchical RCU implementation.
[    0.000000] rcu: RCU calculated value of scheduler-enlistment delay is 10
jiffies.
[    0.000000] NR_IRQS: 33
[    0.000000] rcu: srcu_init: Setting srcu_struct sizes based on
contention.
[    0.000000] clocksource: ccount: mask: 0xffffffff max_cycles: 0xffffffff,
max_idle_ns: 11945377789 ns
[    0.000086] sched_clock: 32 bits at 160MHz, resolution 6ns, wraps every
13421772796ns
[    0.008110] Calibrating delay loop (skipped)... 160.00 BogoMIPS preset
[    0.014370] pid_max: default: 4096 minimum: 301
[    0.021337] Mount-cache hash table entries: 1024 (order: 0, 4096 bytes,
linear)
[    0.026541] Mountpoint-cache hash table entries: 1024 (order: 0, 4096
bytes, linear)
[    0.077044] rcu: Hierarchical SRCU implementation.
[    0.077673] rcu:     Max phase no-delay instances is 1000.
[    0.091972] devtmpfs: initialized
[    0.115533] clocksource: jiffies: mask: 0xffffffff max_cycles:
0xffffffff, max_idle_ns: 19112604462750000 ns
[    0.116804] futex hash table entries: 16 (order: -5, 192 bytes, linear)
[    0.139676] NET: Registered PF_NETLINK/PF_ROUTE protocol family
[    0.156790] platform soc: Fixed dependency cycle(s) with
/soc/intc@600c2000
[    0.219233] clocksource: Switched to clocksource ccount
[    0.266507] NET: Registered PF_INET protocol family
[    0.274408] IP idents hash table entries: 2048 (order: 2, 16384 bytes,
linear)
[    0.294920] tcp_listen_portaddr_hash hash table entries: 1024 (order: 0,
4096 bytes, linear)
[    0.296128] Table-perturb hash table entries: 65536 (order: 6, 262144
bytes, linear)
[    0.303770] TCP established hash table entries: 1024 (order: 0, 4096
bytes, linear)
[    0.309855] TCP bind hash table entries: 1024 (order: 1, 8192 bytes,
linear)
[    0.315629] TCP: Hash tables configured (established 1024 bind 1024)
[    0.326107] UDP hash table entries: 256 (order: 0, 4096 bytes, linear)
[    0.329877] UDP-Lite hash table entries: 256 (order: 0, 4096 bytes,
linear)
[    0.340029] NET: Registered PF_UNIX/PF_LOCAL protocol family
[    0.361833] workingset: timestamp_bits=30 max_order=11 bucket_order=0
[    2.712542] 60000000.serial: ttyS0 at MMIO 0x60000000 (irq = 1, base_baud
= 0) is a ESP32 UART
[    2.714408] printk: console [ttyS0] enabled
[    2.714408] printk: console [ttyS0] enabled
[    2.720147] printk: bootconsole [esp32uart0] disabled
```

```
[    2.720147] printk: bootconsole [esp32uart0] disabled
[    2.759786] physmap-flash 42830000.flash: physmap platform flash device:
[mem 0x42830000-0x4302ffff]
[    2.761481] 2 fixed-partitions partitions found on MTD device
42830000.flash
[    2.765620] Creating 2 MTD partitions on "42830000.flash":
[    2.772746] 0x000000000000-0x000000300000 : "linux"
[    2.787049] 0x000000300000-0x000000880000 : "data"
[    2.787809] mtd: partition "data" extends beyond the end of device
"42830000.flash" -- size truncated to 0x500000
[    2.814687] NET: Registered PF_PACKET protocol family
[    3.044471] cramfs: checking physical address 0x42b30000 for linear
cramfs image
[    3.045351] cramfs: linear cramfs image on mtd:data appears to be 1808 KB
in size
[    3.052366] VFS: Mounted root (cramfs filesystem) readonly on device
31:1.
[    3.057890] devtmpfs: mounted
[    3.062212] Freeing unused kernel image (initmem) memory: 12K
[    3.064482] This architecture does not have kernel memory protection.
[    3.072536] Run /sbin/init as init process
[    3.074991]   with arguments:
[    3.077870]     /sbin/init
[    3.081602]   with environment:
[    3.083725]     HOME=/
[    3.086028]     TERM=linux
Starting syslogd: OK
Starting klogd: OK
Running sysctl: OK
seedrng: can't create directory '/var/lib/seedrng': Read-only file system
Starting network: OK

Welcome to Buildroot
buildroot login: root
~ # cat /proc/cpuinfo
CPU count       : 1
CPU list        : 0
vendor_id       : Tensilica
model           : Xtensa LX7.0.12
core ID         : LX7_ESP32_S3_MP
build ID        : 0x90f1f
config ID       : c2f0fffe:23090f1f
byte order      : little
cpu MHz         : 160.00
bogomips        : 320.00
flags           : nmi debug ocd density boolean loop nsa minmax sext clamps
mac16 mul16 mul32 mul32h fpu s32c1i
physical aregs  : 64
misc regs       : 4
```

```
ibreak          : 2
dbreak          : 2
num ints        : 32
ext ints        : 26
int levels      : 6
timers          : 3
debug level     : 6
icache line size: 4
icache ways     : 1
icache size     : 0
icache flags    :
dcache line size: 16
dcache ways     : 1
dcache size     : 0
dcache flags    :
~ # free
              total        used        free      shared  buff/cache
available
Mem:           7344        3264        3444           0         636
3208

~ #
```

From:
http://wiki.osll.ru/ - **Open Source & Linux Lab**

Permanent link:
http://wiki.osll.ru/doku.php/etc:users:jcmvbkbc:linux-xtensa:esp32s3?rev=1695490175

Last update: **2023/09/23 20:29**