

Hardware notes

ARM-USB-TINY-H

Chip datasheet: http://www.ftdichip.com/Support/Documents/DataSheets/ICs/DS_FT2232H.pdf

Connector pinout

```
      9 5 1
  ----^^----
/0000000000\
\0000000000/
  -----
      6 2
```

Low voltage UART mode

Pin functions

- 1, 2: Vcc (connected)
- 4, 6 and the rest of the low row: GND (connected)
- 5: RX (I)
- 7: CTS# (I)
- 9: TX (O)
- 11: RI# (I)
- 13: RTS# (O)

Driver

- <http://ftdi-usb-sio.sourceforge.net/>
- modprobe ftdi_sio vendor=0x15ba product=0x002a

Xtensa JTAG

Pin functions

- 1: Vcc
- 3: TRST#
- 4: GND
- 5: TDI
- 7: TMS
- 9: TCK
- 13: TDO

- 15: SRST# (doesn't work)

topology.xml controller line

```
<controller id='Controller0' module='ft2232' probe='flyswatter' vid='0x15ba'  
pid='0x002a' usbser='0LVGHYS?' speed='10MHz' />
```

From:

<http://wiki.osll.ru/> - **Open Source & Linux Lab**

Permanent link:

<http://wiki.osll.ru/doku.php/etc:users:jcmvbkbc:hardware?rev=1417282294>

Last update: **2014/11/29 20:31**

